

Shinybow SB-3691 2x1 HDMI PiP/PoP Selector Switch Scaler

- **Type of Switcher:** 2x HDMI Input and 1x HDMI Output Scaler Box
- **HDMI Support:** HDMI 1080p-@60Hz, H36-bit Deep color
- **HDCP/HDMI Support:** HDCP 1.2 Compliant, HDMI 1.3 version
- **Video Bandwidth:** Double Data Rates: 165Mhz, Total 4.95Gbps bandwidth
- **Digital Video Support:** HD: 480i/480p/720p and up to 1080i/p
- **Input:** 2x HDMI (HDMI or DVI digital source)
- **Output:** 1x HDMI (to Destination)
- **Switch Controls:**
 - 1x Select & Function buttons on front panel
 - 1x IR Remote Control (switch control)
 - 1x RS-232
- **Scaling Mode:**
 - Scaler down to 480p
 - Scaler up to 1080p
- **HDMI Signal Booster:** Distance for 1080p cable up to 98 feet (30M)
- **Infrared Frequency:** 38Khz
- **Firmware Update:** Firmware update via RS-232
- **HDMI I/O Connector:** HDMI Type A-SMD 19pin female type
- **Temperature:** Operating Temperature 32°F-100°F (0°C-32°C)
- **Wall Mount:** 1 in High Wall Mount pairs (P/N: WM-1INCH-80mm)
- **Dimensions (LxWxH):** 6.69 x 5.71 x 1.14 in (170x145x29 mm)
- **Power Supply:** DC12V, Powr Input: AC 100~240VAC 50/60Hz (universal type supply)
- **Safety Approvals:** CE, FCC, REACH
- **Product Weight:** 0.677Kgs / 1.5lb