

SECO-LARM MVE-AH030AQ HDMI Extender (Transmitter/Receiver) Kit over Single CAT5e/6 UTP cable with Loop/Audio out

The **ENFORCER** HDMI Extender over Single Cat5e/6 extends the range of traditional HDMI cabling methods by using an active transmitter and receiver to send video and audio over a single Cat5e/6. HDMI formats as large as 1080p can be transmitted up to 196ft (60m) between the two units with zero signal loss by using integrated circuits in the receiver and transmitter.

Features

- **Status LEDs** - Indicate power and HDMI® connection are complete
- **Signal Strength** - Active operation ensures that the signal will remain strong over the length of the cable
- **Distance** - Capable of maintaining a clean HDMI® signal up to 196ft (60m)
- **Formats Supported** - Supports both progressive and interlaced formats: 1080p/1080i/720p/576p/576i/480p/480i
- **Plug and Play** - Comes as a complete set consisting of a transmitter and receiver, power supplies, and IR extenders
- **Zero Signal Loss** - Integrated circuits in the transmitter and receiver clean, buffer, and amplify the HDMI signal to prevent signal loss and ensure a clear signal regardless of the length of the cable
- **Bi-directional IR** - Send IR signals from the source to the monitor or from the monitor to the source for discrete operation of devices
- **EDID Management** - Eliminate sync issues by choosing from 9 different internal EDID settings, the HDMI® loop display, or the main HDMI display
- **Digital Audio Out** - Send HDMI® audio directly to an external sound bar or A/V Receiver
- **ARC Option Switch** - Enable Audio Return Channel (ARC) to automatically switch the audio source to that shown by the display device
- **HDMI® Loop Output** - Secondary HDMI® output for local displays